

FRITZ!DECT Repeater 100

Technical data

Highlights at a glance

- Increases the range of your cordless telephones
- With integrated socket
- Radio connections secure ex works
- Simple operation launch
- Ideal for FRITZ!Box with a DECT base station or any other DECT base station repeater function



Technical specifications

Features

- Expands reception and transmission range for DECT cordless telephones and services.
- Telephone calls bug-proof through encryption using FRITZ!Box as the base station
- Up to three calls possible simultaneously
- Supports automatic handover of DECT telephone calls, so that a call in progress can be switched between the base station and the repeater at any time
- Repeater function even for HD telephony, web radio and RSS with FRITZ!Box as the base station
- Range can be expanded in any direction with additional FRITZ!DECT Repeaters
- Compatible with DECT base stations compliant with the GAP standard (basic functions) and with repeater function enabled
- Integrated socket – no plug space lost
- Quick operation launch: Switch on and press DECT button on FRITZ!Box
- Information on operating status of repeater indicated on DECT Monitor of the FRITZ!Box
- DECT switch: Register/deregister repeater with the base station
- Status switch: Turn LEDs on repeater on/off
- Automatic operating software updates over the FRITZ!Box

Interfaces

- Connection to mains with 230V, 50 Hz to socket for Type F socket (Schuko, CEE 7/4)
- DECT wireless standard
- Connected devices up to 2,300 W / 10 A

System requirements

- 230-volt outlet
- FRITZ!Box with DECT and FRITZ!OS 5.50 (or higher) or any other DECT base station repeater function (GAP)

Package contents

- FRITZ!DECT Repeater 100
- Quick Guide

Article number

- 20002641